



Power Inverter Modified Sine Wave 24 VDC - AC 230 V 150 W F (CEE 7/3) / USB

General information

Inverter for 24 V battery of a car and boat. It will invert the 24 V DC current to 230 V AC. With this device 230 V equipment can be connected anywhere! The inverter is equipped with a very high peak output power. Due to the USB port it is even possible to use sensitive USB equipment such as MP3-players and digital cameras.

Specifications

Height:	69 mm
Width:	94 mm
Input type:	Cigarette lighter plug
Output peak power:	300 W
Fuse:	Yes
Works with remote control:	No
Output voltage:	AC 230 V
Efficiency:	90 %
Safety functions:	Low-Battery Shutdown Protection
Safety functions:	Thermal Protection
Safety functions:	Output Short-Circuit Protection
Safety functions:	Overload Protection
Safety functions:	Too High Input Voltage Protection
Safety functions:	Reverse Battery-Polarity Protection
Weight:	430 g
Output waveform:	Modified sine wave
Input voltage:	24 VDC
Output power:	150 W
Voltage:	AC 230 V
Number of sockets:	2
Socket type:	F (CEE 7/3)
Socket type:	USB
Length:	165 mm



Sales information

Order code:	HQ-INV150WU-24
Product description:	Power Inverter Modified Sine Wave 24 VDC - AC 230 V 150 W F (CEE 7/3) / USB
Packaging:	Giftbox
Brand name:	HQ



Quantity	LxWxH (mm)	Weight
1	130x85x190	755 gr.
16	290x365x390	12810 gr.