

HCS-3400-Series housing are available in Light grey (Pantone 428C) / Dark grey (Pantone 426C)

To Roccial Control of the Control of

Description

This range of high graded SMPS is designed for a wide range of applications for telecommunications, laboratory and industry.

The power efficient circuit designs allow units to have small form factor with low profile and small footprint casings.

The intelligent fan speed control program checks the fan at power on and adapts the right speed to ensure a quiet and safe operation of the power supply at different ambient temperatures and power output levels.

The dual action (coarse & fine set) control knobs make tuning the voltage and current level ever so smooth, precise and fast, due to the rotary encoder and microprocessor control. Setting the CC current limiting can be done in open circuit at output poles.

The isolated ground construction allow parallel and series connection of power supplies with ease and safety.

The three user defined presets of voltage and current limiting levels facilitate quick access to frequently used VI settings. The full remote control functionality offer a wide range of operation possibilities for the industrial and more sophisticated users.

We add an USB port for access to computer to run cyclical operation with programmable voltage, current, period time and cycles.

Features

- Rotary Encoder Control Knob with coarse & fine tuning
- 3 user defined V & I presets
- High RFI immunity & excellent EMI
- Isolated ground, Active PFC & high power efficiency
- Intelligent fan control from zero to full speed
- Over load, Over Temperature & Tracking Over Voltage protections
- Remote Programmable via USB to computer.
- Wired Remote Control of V, I, & output On-Off without computer.
- 20 programmable sets of V, I & cycle periods for repetitive operation up to 999 cycles.

Specifications

Output Variable Output Voltage 1 - 16VDC 1 - 32VDC 1 - 60VDC Variable Output Current 0 - 40A 0 - 20A 0 - 10A Voltage Regulation Load (10 - 100% Load) 50mV Line (170 - 264VAC Variation) 20mV Current Regulation Load (10 - 90% Rated Voltage) 150mA 100mA 100mA Line (170 - 264VAC Variation) 50mA 5mV 5mV Ripple & Noise Ripple & Noise (r.m.s.) Voltage 5mV 5mV 5mV Ripple & Noise (peak-peak) Voltage 50mV 50mV 100mV Switching Frequency 65 - 85Khz~ 75 - 95Khz~ 65 - 85Khz~ Tracking Over Voltage Protections 0/P 1-5V : set voltage +2V O/P 5-20V : set voltage +2V O/P 5-20V : set voltage +3V O/P 5-20V : set voltage +4V O/P 20-60V :	
Variable Output Current 0 - 40A 0 - 20A 0 - 10A Voltage Regulation Load (10 - 100% Load) 50mV Line (170 - 264VAC Variation) 20mV Current Regulation Load (10 - 90% Rated Voltage) 150mA 100mA 100mA Line (170 - 264VAC Variation) 50mA 80mA Ripple & Noise Ripple & Noise (r.m.s.) Voltage 5mV 5mV 5mV Ripple & Noise (peak-peak) Voltage 50mV 50mV 100mV Switching Frequency 65 - 85Khz~ 75 - 95Khz~ 65 - 85Khz~ Tracking Over Voltage Protections 0/P 1-5V : set voltage +2V O/P 1-5V : set voltage +2V O/P 5-16V : set voltage +3V O/P 5-20V : set voltage +3V O/P 5-20V : set voltage +4V O/P 5-20V : set voltage +4V O/P 5-20V : set voltage +4V O/P 20-60V	
Voltage Regulation 50mV Line (170 - 264VAC Variation) 20mV Current Regulation 150mA 100mA 100mA Line (170 - 264VAC Variation) 50mA 50mA Ripple & Noise 5mV 5mV 5mV Ripple & Noise (r.m.s.) Voltage 50mV 50mV 100mV Switching Frequency 65 - 85Khz~ 75 - 95Khz~ 65 - 85Khz~ Tracking Over Voltage Protections O/P 1-5V : set voltage +2V O/P 5-20V : set voltage +2V O/P 5-20V : set voltage +3V O/P 5-20V : set voltage +4V O/P 20-32V : set voltage +4V O/P 20-60V : set voltage +	
Load (10 - 100% Load) 50mV	
Line (170 - 264VAC Variation) 20mV Current Regulation 150mA 100mA 100mA Line (170 - 264VAC Variation) 50mA 100mA 100mA Ripple & Noise Fipple & Noise (r.m.s.) Voltage 5mV 5mV 5mV Ripple & Noise (peak-peak) Voltage 50mV 50mV 100mV Switching Frequency 65 - 85Khz~ 75 - 95Khz~ 65 - 85Khz~ Tracking Over Voltage Protections 0/P 1-5V : set voltage +2V O/P 5-20V : set voltage +2V O/P 5-20V : set voltage +3V O/P 5-20V : set voltage +4V O/P 20-60V : set voltage +4	
Current Regulation Load (10 - 90% Rated Voltage) 150mA 100mA 100mA Line (170 - 264VAC Variation) 50mA Ripple & Noise Fripple & Noise (r.m.s.) Voltage 5mV 5mV 5mV Ripple & Noise (peak-peak) Voltage 50mV 50mV 100mV Switching Frequency 65 - 85Khz~ 75 - 95Khz~ 65 - 85Khz~ Tracking Over Voltage Protections O/P 1-5V : set voltage +2V O/P 5-20V : set voltage +3V O/P 5-20V : set voltage +3V O/P 5-20V : set voltage +4V O/P 20-60V : set voltage +	
Load (10 - 90% Rated Voltage) 150mA 100mA 100mA 100mA	
Line (170 - 264VAC Variation) 50mA	
Ripple & Noise SmV 5mV 5mV Ripple & Noise (peak-peak) Voltage 50mV 50mV 100mV Switching Frequency 65 - 85Khz~ 75 - 95Khz~ 65 - 85Khz~ Tracking Over Voltage Protections O/P 1-5V : set voltage +2V O/P 5-20V : set voltage +2V O/P 5-20V : set voltage +3V O/P 5-20V : set voltage +4V O/P 20-32V : set voltage +4V O/P 20-60V : set	
Ripple & Noise (r.m.s.) Voltage 5mV 5mV Ripple & Noise (peak-peak) Voltage 50mV 50mV Switching Frequency 65 - 85Khz~ 75 - 95Khz~ 65 - 85Khz~ Tracking Over Voltage Protections O/P 1-5V : set voltage +2V O/P 5-20V : set voltage +2V O/P 5-20V : set voltage +3V O/P 5-20V : set voltage +4V O/P 20-32V : set voltage +4V O/P 20-60V : s	
Ripple & Noise (peak-peak) Voltage 50mV 50mV 100mV Switching Frequency 65 - 85Khz~ 75 - 95Khz~ 65 - 85Khz~ Tracking Over Voltage Protections O/P 1-5V : set voltage +2V O/P 5-16V : set voltage +3V O/P 5-20V : set voltage +3V O/P 5-20V : set voltage +4V O/P 20-32V : set voltage +4V O/P 20-60V : s	
Switching Frequency	
Tracking Over Voltage Protections O/P 1-5V : set voltage +2V O/P 5-16V : set voltage +3V O/P 5-20V : set voltage +3V O/P 5-20V : set voltage +3V O/P 20-32V : set voltage +4V O/P 20-60V : set voltage +4V O/P	
O/P 5-16V : set voltage +3V O/P 5-20V : set voltage +3V O/P 5-20V : set voltage +4V O/P 5-20V : set voltage +4V O/P 5-20V : set voltage +4V O/P 20-60V : set voltage +4V	
Voltage Meter 3 Digit LED Display ±(0.2% +3counts) Current Meter 3 Digit LED Display ±(0.2% +3counts) Input Voltage 200 - 240VAC 50/60Hz~ (or on request) Full Load Input Current 3.15A 3.1A 3.1A Efficiency 85.5% 87% 89%	tage +3V
Current Meter 3 Digit LED Display ±(0.2% +3counts) Input Voltage 200 - 240VAC 50/60Hz~ (or on request) Full Load Input Current 3.15A 3.1A 3.1A Efficiency 85.5% 87% 89%	
Input Voltage 200 - 240VAC 50/60Hz~ (or on request) Full Load Input Current 3.15A 3.1A 3.1A Efficiency 85.5% 87% 89%	
Full Load Input Current 3.15A 3.1A 3.1A Efficiency 85.5% 87% 89%	
Efficiency 85.5% 87% 89%	
Power Factor Control Power factor correction >0.95 at optimal load	
Cooling Method Thermostatic Control Fan from Zero to full speed	
Protections Overload, Short Circuit by Constant Current, Output Tracking Over Voltage, Over Temperature	
Special Features 3 User defined V & I preset, Remote control V, I and output on-off	
Preset Cycle Programming Max. 20 presets of V & I, ; Max. preset cycle 999	
Approvals CE EMC: EN 55011, 55022 LVD: EN 60950, 61010	
Dimensions (WxHxD) 200x90x215 mm 7.9x3.5x8.5 inch	
Weight 2.6 kg 5.7 lbs	

- All values are based on the Standard ambient Temperature 25°C and Pressure 0.1 Mpa.
- SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT PRIOR NOTICE