

Test Charger



Features

- Controlled by microcomputer, this charger can charge Li-Ion batteries under fast way
- The 500 mA and 1000 mA charging currents are adapted to different battery sizes
- Protects against overcharging, short-circuits, and reverse charging. Also detects faulty batteries
- LED indicator shows the charging status
- The charger can be charged via notebook, power bank, phone adapter with USB cable
- Used for 3.7 V Li-Ion battery: (10440, 10500, 12500, 12650, 13450, 13500, 13650, 14500, 14650, 16500, 16650, 17500, 17650, 18490, 18500, 18650, 18700, 20700, 21700, 22500, 22650, 25500, 26500, 26650)
- It can charge 71 mm length 18650 batteries with protection boards



Specification

Input	5 VDC / 1 A or 2.1 A
Power Consumption	13.5 W max.
Battery Type	Li-Ion
Charging Slots	2
Charge Current	500 mA / 1 A
USB Output	No
Protection Against Short Circuiting	Yes
Protection Against Over-Heating	No
Protection Against Over-Charging	Yes
Maximum Time Protection	Yes
LCD or LED	LED
Dimensions (L x W x H)	99.5 x 60 x 28 mm
Weight	54 g

Art. Nr.

RND 305-00027