



## 93560

### Digital light meter with save function

#### Functions

- Illuminance measurement

#### Product information

- Automatic range selection
- Silicon sensor
- Integrated measurement memory (data hold)

#### Product highlights

- Measurement memory for 99 individual readings

### Technical specifications

Display	LCD, 4 digit
Measurement ranges (Auto range)	0...50 lx, 0...500 lx, 0...5000 lx, 0...50 klx, 0...200 klx
Resolution of the display	0.01 lx, 0.1 lx, 1 lx, 10 lx, 100 lx
Measurement ranges	0...5, 0...50, 0...500, 0...5000 fc, 0...20 kfc
Accuracy	< 10 %
Temperature drift	< 1%/K
Power supply	6 x battery 1.5 V, IEC LR03
Dimensions	150 x 72 x 35 mm (unit) 92 x 60 x 29 mm (sensor)
Weight	approx. 250 g

### Included:

- 1 x 93560
- 6 x battery 1.5 V, IEC LR03
- 1 x carrying case
- 1 x user manual

### Ordering Information:

Description	Model	Article no.
93560	93560	3222543



## LM-100

### Digital Lux Meter

#### Functions

- Light measurement

#### Product information:

- Manual range selection
- Silicon sensor
- Integrated measurement memory (data hold)
- Max data hold (Max)

## LM-120

### Digital Lux Meter

as the LM-100, also with:

- Automatic and manual range selection
- Minimum and maximum data hold (min/max)
- Auto Power Off
- Zero adjust knob

### Technical specifications

Display	LCD, 3½ digit
Measurement range	0...20 (only LM-120) 0...200, 2000, 20.000, 200,000 Lux 0-20, 200, 2000, 20,000 fc
Resolution	0.1, 1, 10, 100 Lux 0.01, 0.1, 1, 10 Fc
Accuracy	< 10 %
Power supply	1 x battery 9 V, IEC 6F22
Dimensions	130 x 63 x 38 mm (unit) 80 x 55 x 29 mm (sensor)
Weight	approx. 220 g

### Included:

- 1 x LM-100 or LM-120
- 1 x battery 9 V, IEC 6F22
- 1 x carrying case
- 1 x user manual

### Ordering Information:

Description	Model	Article no.
LM-100	LM-100	3052348
LM-120	LM-120	3052353