

PRODUCT-DETAILS

MS325/2.5-S

MS325/2.5-S Motor Starter



General Information

Extended Product Type	MS325/2.5-S
Product ID	2CCF004155R0001
EAN	7612270029341
Catalog Description	MS325/2.5-S Motor Starter
Long Description	The MS325 is a circuit- breaker with a motor protection charakteristik. It is intendend above all for industrial applications (MCC) or in distribution systems without a back up fuse.

Ordering

Minimum Order Quantity	1 piece
Customs Tariff Number	85365000

Popular Downloads

Data Sheet, Technical Information	9AKK107492A6192
Instructions and Manuals	No document needed
Dimension Diagram	9AKK107492A6192

Dimensions

Product Net Width	94.5 mm
-------------------	---------

Product Net Height	90 mm
Product Net Depth / Length	54 mm
Product Net Weight	340 g

Technical

Rated Operational Power AC-3 (P _e)	(400 V) 2 kW
Rated Operational Voltage	230...400 V
Rated Operational Current (I _e)	1.6 ... 2.5 A
Power Loss	2.04 W
Number of Poles	3
Degree of Protection	IP20
Standards	IEC60947-2 IEC 60947-4-1

Environmental

Ambient Air Temperature Compensation	Yes
RoHS Status	Following EU Directive 2002/95/EC August 18, 2005 and amendment

Certificates and Declarations (Document Number)

Declaration of Conformity - CE	1SAD938518-0003
Environmental Information	2CCC404013D0201
Instructions and Manuals	No document needed
RoHS Information	2CCC413008D0206_RoHS

Container Information

Package Level 1 Units	carton 1 piece
Package Level 1 Width	54 mm
Package Level 1 Depth / Length	58 mm
Package Level 1 Height	80 mm
Package Level 1 Gross Weight	362 g
Package Level 1 EAN	7612270029341

Classifications

Object Classification Code	FC
ETIM 4	EC000074 - Motor protective circuit-breaker
ETIM 5	EC000074 - Motor protective circuit-breaker
ETIM 6	EC000074 - Motor protection circuit-breaker
ETIM 7	EC000074 - Motor protection circuit-breaker
E-Number (Switzerland)	500400065

Categories

Low Voltage Products and Systems → Circuit Breakers → Manual Motor Starters

Low Voltage Products and Systems → Control Products → Manual Motor Starters → Manual Motor Starters

Low Voltage Products and Systems → Modular DIN Rail Products → Plug-in Distribution Systems → Others

