

PRODUCT-DETAILS

## F204 A S-63/0.3 F204 A S-63/0.3 Residual Current Circuit Breaker



General Information		
Extended Product Type	F204 A S-63/0.3	
Product ID	2CSF204201R3630	
EAN	8012542784807	
Catalog Description	F204 A S-63/0.3 Residual Current Circuit Breaker	
The RCCBs F200 series assures protection to people and installations against fa Long Description to earth. A large offer for standard instantaneous and selective AC and A types is with some configurations for special a		

Technical	
Standards	IEC/EN 61008
	UL 1053
Type of Residual Current	A type
Rated Voltage $(U_r)$	230/400 V
Rated Operational Voltage	230 / 400 V AC
Rated Insulation Voltage	500 V
$(U_i)$	
Rated Impulse Withstand	4 kV
Voltage (U <sub>imp</sub> )	
Input Voltage Type	AC
Rated Current (I <sub>n</sub> )	63 A

Rated Residual Current	300 mA	
Rated Conditional Short- Circuit Current (I <sub>nc</sub> )	10 kA	
Rated Service Short- Circuit Breaking Capacity (I <sub>cs</sub> )	1 kA	
Maximum Surge Current	5 kA	
Leakage Current Type	A	
Rated Frequency (f)	50 / 60 Hz	
Power Loss	at Rated Operating Conditions per Pole 4.4 W	
Power Supply Connection	Arbitrary	
Electrical Endurance	10000 cycle	
Number of Poles	4	
Operating Characteristic	Selective	
Position of Neutral Terminals	Right	
Mounting Type	DIN rail	
Options Provided	None	
Accessories Available	Yes	
Connecting Capacity	Busbar 10 mm² Rigid 25 25 mm² Flexible 25 25 mm²	
Rated Cross-Section	4 - Multi-Wired 025 mm² 1 - Solid-Core 2525 mm²	
Environmental		
Ambient Temperature	-2555 °C	
Ambient Air Temperature	Operation -2555 °C	
Degree of Protection	IP2X	
Pollution Degree	2	
Resistance to Vibrations acc. to IEC 60068-2-6	0.1 mm or 1 g - 20 cycles at 51505 Hz	
Resistance to Shock acc. to IEC 60068-2-27	25g / 2 shocks / 13 ms	
RoHS Status	Following EU Directive 2011/65/EU	
Environmental Information	Refer to RoHS	
Technical UL/CSA		
Maximum Operating Voltage UL/CSA	480Y / 277 V AC	
Short-Circuit Current Rating (SCCR)	300 mA	
Pinnering and a second a second and a second a second and		
Dimensions	_	
Width in Number of Modular Spacings	4	
Product Net Width	0.070 m	
Product Net Height	0.085 m	

Product Net Depth /	0.069 m
Length	
Product Net Weight	0.360 kg
Built-In Depth (t <sub>2</sub> )	69 mm

Container Information	
Package Level 1 Units	box 1 piece
Package Level 1 Width	80 mm
Package Level 1 Height	41 mm
Package Level 1 Depth / Length	94 mm
Package Level 1 Gross Weight	0.415 kg
Package Level 1 EAN	8012542784807
Package Level 2 Units	box 3 piece
Package Level 2 Width	96 mm
Package Level 2 Height	85 mm
Package Level 2 Depth / Length	240 mm
Package Level 2 Gross Weight	1230 g
Package Level 2 EAN	8012542784814

Ordering	
Minimum Order Quantity	1 piece
Customs Tariff Number	85363030
E-Number (Finland)	3259504
E-Number (Sweden)	2160151
Country of Origin	Italy (IT)

Declaration of Conformity - CE	9AKK106713A5602
Environmental Information	Refer to RoHS
Instructions and Manuals	9AKK107991A6127
RoHS Information	2CSC423001K2702

Popular Downloads	
Data Sheet, Technical Information	9AKK107991A8329
Instructions and Manuals	9AKK107991A6127

## Classifications

ETIM 7 EC000003 - Residual current circuit breaker (RCCB)

ETIM 8	EC000003 - Residual current circuit breaker (RCCB)	
EPLAN Catalog Tree	Electrical engineering / Protection devices / Ground fault current circuit breaker	
EPLAN Function Definition	Ground fault current circuit-breaker / Ground fault current circuit breakers, 8 connection points / Ground fault current circuit breaker, four-pole 1_2_3_4_5_6_N_N.	
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)	
WEEE B2C / B2B	Business To Consumer	
CN8	85363030	
Object Classification Code	F	

Accessories				
Identifier	Description	Туре	Quantity	Unit Of Measure
2CDS200912R0001	S2C-H6R Auxiliary Contact	S2C-H6R	2	piece
2CDS200922R0001	S2C-S/H6R Signal / Auxiliary Contact	S2C-S/H6R	2	piece
2CDS200946R0001	S2C-H6-11R Auxiliary Contact	S2C-H6-11R	1	piece
2CDS200946R0003	S2C-H6-02R Auxiliary Contact	S2C-H6-02R	1	piece
2CDS200946R0002	S2C-H6-20R Auxiliary Contact	S2C-H6-20R	1	piece
2CSS200933R0011	F2C-A1 Shunt trip	F2C-A1	1	piece
2CSS200933R0012	F2C-A2 Shunt trip	F2C-A2	1	piece
2CSS200911R0005	S2C-UA 230 AC Undervoltage release	S2C-UA 230 AC	1	piece
2CSS200911R0007	S2C-UA 24 DC Undervoltage release S	S2C-UA 24 DC	1	piece
2CSS200911R0002	S2C-UA 24 AC Undervoltage release S	S2C-UA 24 AC	1	piece
2CSS200911R0008	S2C-UA 48 DC Undervoltage release 9	S2C-UA 48 DC	1	piece
2CSS200911R0004	S2C-UA 110 AC Undervoltage release	S2C-UA 110 AC	1	piece
2CSS200911R0006	S2C-UA 400 AC Undervoltage release	S2C-UA 400 AC	1	piece
2CSS200911R0001	S2C-UA 12 DC Undervoltage release S	S2C-UA 12 DC	1	piece
2CSS200911R0010	S2C-UA 230 DC Undervoltage release	S2C-UA 230 DC	1	piece
2CSS200911R0009	S2C-UA 110 DC Undervoltage release	S2C-UA 110 DC	1	piece
2CSS200911R0003	S2C-UA 48 AC Undervoltage release s	S2C-UA 48 AC	1	piece
2CSS200910R0005	S2C-OVP1 Overvoltage release	S2C-OVP1	1	piece
2CSS200993R0005	S2C-OVP2 Overvoltage release	S2C-OVP2	1	piece
2CSF200997R0013	F2C-CM Motor operating device	F2C-CM	1	piece
2CSF200996R0013	F2C-ARI Auto-reclosing unit	F2C-ARI	1	piece

## Categories

F204 A S-63/0.3 5





