PWM	CRX2	CS1	RX1	0		GND
PWM	CTX2	MISO1	TX1	1		5V
PWM	OUT2			2		
PWM	LRCLK2			3		
PWM	BCLK2			4		
PWM	IN2			5		
PWM	OUT1D			6		
PWM	OUT1A		RX2	7		
PWM	IN1		TX2	8		
PWM	OUT1C			9		
PWM	MQSR	CS		10		
PWM	CTX1	MOSI		11		
PWM	MQSL	MISO		12		

GND — 0 ... 5V Vin (3.6 to 5.5 volts)
GND
3.3V (250 mA max)

All digital pins have interrupt capability.

23	A9		CRX1	MCLK1	PWM
22	A8		CTX1		PWM
21	A7	RX5		BCLK1	
20	A6	TX5		LRCLK1	
19	A5			SCL	PWM
18	A4			SDA	PWM
17	A3	TX4		SDA1	
16	A2	RX4		SCL1	
15	A1	RX3	S/PDIF IN	PWM
14	A0	TX3	S/PDIF OUT	PWM
13	(LED)	SCK		PWM

3.3V

MIMXRT1062
DVJ6A
0N00X
CTAB1905G

PWM	SCL2		TX6	A10	24
PWM	SDA2		RX6	A11	25
		MOSI1		A12	26
		SCK1		A13	27
PWM			RX7		28
PWM			TX7		29
	CRX3				30
	CTX3				31
	OUT1B				32

GND

41	A17			
40	A16			
39	A15	MISO1	OUT1A
38	A14	CS1	IN1
37		CS		PWM
36		CS		PWM
35		TX8		
34		RX8		
33			MCLK2	PWM