

Acer H series

Acer H7550ST

Rich colours and excellent picture quality for your home cinema



- Resolution: 1080p Full HD (1,920 x 1,080 px)
- Brightness: 3,000 (standard), 2,400 (eco) ANSI lumens
- Contrast: 16,000:1
- Lamp life (hr.): 4,000 (standard), 6,000 (eco), 8,000 (ExtremeEco)
- Warranty: 2 years PickUp service, 1 year for the lamp, 5 years for the DLP Chip
- Usage recommendation: Home cinema



















SPECIFICATIONS Acer H7550ST







Ordering Information

Model H7550ST Part Number MRJKY11.00L FAN 4713147709984

Technical Specifications

Projection technology

DLP Chip DarkChip™ 3 DMD Version Resolution **Display Format**

Contrast Displayable Colours

Brightness 3,000 (standard), 2,400 (eco) ANSI lumens Focus / Focal distance

Projection size (diagonal) 1.37 ~ 7.62 m Projection distance Throw ratio Zoom / Digital-Zoom 1:1.1x/2x

Image Offset 106 %

Horizontal / Vertical frequency

Projection Modes

Lamp / type Lamp life (hr.)

Keystone Correction Speaker

Weight / incl. packaging (kg) Dimensions / Shipping dimensions (mm)

Power Consumption

Noise level Uniformity (%) DLP 3D Ready & nVIDIA 3DTV Play & HDMI

0.65" BrilliantColor™

1080p Full HD (1,920 x 1,080 px) 16:9 (native) / 4:3 (supported)

1.07 Billion Colors

F = 2.60 ~ 2.78 / f = 10.20 ~ 11.22 mm

0.90 ~ 4.60 m 0.69~0.76:1

15 ~ 100 kHz/24 ~ 120 Hz

Front- / Rear- & Front-Ceiling- / Rear-

Ceiling-Projection

210 watt Osram UHP

4,000 (standard), 6,000 (eco), 8,000 (ExtremeEco)

+/- 40° (vertical) manual & automatic 2x 10 watt (DTS Sound, Bluetooth speakers

& headphones supported)

3.40 kg /6.40 kg 357 x 241 x 98 /470 x 250 x 415

269 (standard), 210 (eco), < 0.5 watt (standby)

33 (standard), 30 (eco) dB

85 %

Input Ports

HDMI with HDCP 1x HDMI / MHL with HDCP 2x VGA analog D-Sub 1x Composite Video RCA 1x Component (3 RCA) 1x S-Video Mini DIN 1x Audio in (3.5mm) 1x

Output Ports

1x DC Out 5V USB Type A Audio out (3.5 mm) D-Sub Out (for Monitor Loop Through) 1x

USB Type B mini 1x RS232 1x USB B (Remote Computer Control) 1x

PIN security card PIN security Power adapter IEC 320 C13 1x (Euro-plug) VGA cable 15pol 1x (1.8 m)

IR remote control incl batteries 1x (PgUp / PgDown & freeze function)

white

Lens cap 1x User Manual on CD 1x **Ouick Start Guide** 1x

Other accessories 1x 3D glasses

Spare lamp 4713147561209 / MC.JKY11.001 4713147892877 / MC.JLC11.002 Universal ceiling mount short 4713147892884 / MC.JLC11.003 Universal ceiling mount long Acer 3D Shutterbrille 4713147532261 / MC.JFZ11.00B Acer WirelessHD Kit 4713147715251 / MC.JKY11.009 Acer CastMaster Buttons 4710180557206 / MC.40511.00N Acer Wireless Mirror 4713883764520 / MC.JQC11.008 4710180784336 / MC.40511.00Y Acer CastMaster Touch

Warranty 2 years PickUp service, 1 year for the lamp,

5 years for the DLP Chip

Usage recommendation

Usage recommendation Home cinema



Acer H7550ST SPECIFICATIONS

Projection Distance Calculator

Projection Distance Calculator

www.acer.com/ac/de/CH/content/acer-projection-calculator



Acer H7550ST

ACCESSORIES AND FEATURES

Acer ColorBoost 3D



ColorBoost 3D

Acer ColorBoost 3D: Acer ColorBoost 3D is the innovative combination of a continuously improved image processing algorithm, the latest DLP chipset, an optimized design of the 6-segment color wheel and advanced lighting control technology. As a result, Acer projectors are able to project absolutely lifelike colors throughout their life cycle - in both 2D and 3D modes.

Acer Color Safe II



Acer ColorSafe II guarantees consistent, brilliant and natural color projection throughout the life of the projector. This is ensured by the use of DLP® technology and a 5-year warranty

on the DLP® chip. Projectors without DLP® technology experience a decrease in colour brilliance over time.

AC Power On



AC power on

With the AC Power On function, the projector is able to turn on automatically when the projector is powered. You no longer need to turn on the projector separately, but can start the projector directly, for example by turning on the power in the meeting room.

Auto Ceiling Mount Correction



Auto Ceiling-Mount Correction: The built-in gravity sensor in the Acer projector detects when the projector is mounted overhead on a ceiling and automatically rotates the projection 180° without any additional menu adjustments.

Automatic Keystone Correction



Thanks to the automatic vertical keystone correction, the Acer projector automatically compensates for trapezoidal distortion if the projector is not positioned exactly vertically and projects a rectangular image.

Bluetooth Audio



Can one projector be just one projector? No! Thanks to Bluetooth Audio, you can connect your notebook, tablet or smartphone to the projector via Bluetooth and turn it into a music box.

Who needs a jukebox when you can have a projector?

Customizable startup screen



CUSTOMIZABLE STARTUP SCREEN

The Customizable Startup Screen allows you to create an individual startup screen per screenshot. This startup screen, no matter if it is the business user's company logo or a home user's favorite photo, is automatically displayed when the projector is started.

Customizable startup screen



CUSTOMIZABLE STARTUP SCREEN

The Customizable Startup Screen allows you to create an individual startup screen per screenshot. This startup screen, no matter if it is the business user's company logo or a home user's favorite photo, is automatically displayed when the projector is started.

HDMI 3D



HDMI 3D: The integrated HDMI 1.4a standard allows 3D content to be transferred from suitable playback devices such as 3D Blu-ray players, 3D set-top boxes and 3D game consoles without the need for an additional PC. For example, Acer 3D shutter glasses Bluray 3D movies and 3D TV shows can be viewed in your living room up to 7.62 meters (300") diagonal.

nVIDIA 3DTV Play ready



With the nVIDIA 3DTV Play ready function, the user can play and view any nVIDIA 3D Vision compatible game, compatible pictures and movies and frame sequential content from the PC with appropriate software.

Acer Smart Format Technology



SmartFormat

Acer SmartFormat technology supports a wide range of input signals, eliminating the need for switching on your notebook/PC, DVD player and receiver. Signals up to 1080p can be received by Acer ColorBoost projectors with HDMI* using Acer SmartFormat technology and can be played back in compressed form.

*Depends on model

Original 24p



Experience true cinema at 24 frames per second. The Acer Blu-Ray projector reproduces films in the original cinema format as they were shot on the film set. See 24p movies through the eyes of the director.



Acer H7550ST

ACCESSORIES AND FEATURES

Instant Pack



InstantPack guarantees the lamp safety of Acer ColorBoost projectors. The current lamps from renowned manufacturers such as Osram and Philips are not damaged in the event of a sudden loss of power. (Acer recommends that the projector be powered until the fan stops) The lamp warranty is 1 year with no hour limit.

Installation monu



With the help of the installation menu, the Acer projector can be perfectly aligned with the surface to be projected in no time at all. The Installation menu can be accessed by pressing the Menu button even if no source is connected to the projector.

Quick Detection



The Quick Detection function quickly, reliably and automatically detects the connected source and immediately displays the image. Supported by SmartFormat technology, the projector can project immediately without any major adjustments.

MHL Connectivity



The MHL connectivity (via the MHL™/HDMI™ port) allows you to transmit an uncompressed digital HDMI signal from your smartphone while it is charging via the port. Using the unique optional Acer MHL wireless adapter, content can even be wirelessly transferred from a video source to the projector via Miracast WiFi Display, WiDi Wireless Display or DLNA.

Wall Color Compensation



Wall-Color Compensation: Best image quality enables wall color correction on colored projection surfaces such as blackboards and wallpaper. 5 optimised wall colours can be compensated easily and without any further settings via the menu for best picture quality.

PIN Security



Acer PIN Security provides the ability to set a PIN to protect the Acer projector from unauthorized use and theft. A lost PIN can only be reset by the Acer Service after ownership verification.

Auto Shutdown



The Auto Shutdown function automatically shuts down the Acer projector, if no input signal is received after a preset time. This function can be set individually via the menu and helps to save power and lamp hours.

Hidden Dongle Design



Acer Hidden Port Design: The Acer Hidden Port is located under the lid of the case and offers the possibility to connect the Acer WirelessCAST MWA3 or the Acer WirelessHD-Kit MWiHD1 to the HDMI/MHL connection there and to project wirelessly. The Google Chromecast, for example, is also supported thanks to the micro-USB power supply.

Short Throw Distance



Short Distance Projection: Thanks to Short Distance Projection, you can project an incredibly large image even at the smallest projection distance.

Short Distance projectors are particularly suitable for schools or conference rooms, but also for any room with limited size. Thanks to short distance, you don't have to do without a projection experience even in small rooms.