







Model Number

NCN3-F31-N4-V18

Features

- Direct mounting on standard actuators
- Compact and stable housing
- **Fixed setting**
- EC-Type Examination Certificate TÜV99 ATEX 1479X
- Usable up to SIL2 acc. to IEC 61508

Accessories

BT65A

Activator for F31 series

BT65X Activator for F31 series

BT115A

Activator for F31 series

BT115X Activator for F31 series

BT65B Activator for F31 series

BT115B

V18-W

Cable socket in M18 format, ready for make up

Technical Data General specifications

Switching element function		DC	Dual NC
Rated operating distance	s _n	3 mm	
Installation		flush mounta	able
Output polarity		NAMUR	
Assured operating distance	sa	0 2.4 mm	
Actuating element		Stainless ste	el 1.4305 / AISI 303
		8.5 mm x 8.5	mm x 0.5 mm

Reduction factor r_{Al} 0.5 Reduction factor r_{Cu} Reduction factor r₃₀₄ 0.4 1 1.3 Reduction factor r_{St37} Reduction factor r_{Brass} 0.6 **Nominal ratings**

Nominal voltage 8 V 0 ... 3 kHz Switching frequency typ. 5 % Hysteresis

Reverse polarity protection reverse polarity protected Short-circuit protection

Suitable for 2:1 technology yes , Reverse polarity protection diode not required Current consumption Measuring plate not detected ≥ 3 mA

≤ 1 mA Measuring plate detected Time delay before availability ≤ 1.1 ms Switching state indicator LED, yellow

Functional safety related parameters

 MTTF_d 1470 a Mission Time (T_M) 20 a 0 % Diagnostic Coverage (DC)

Ambient conditions

Ambient temperature -25 ... 100 °C (-13 ... 212 °F)

Note:

Under the same product name but with a different part no., this product has a predecessor with a restricted temperature range (up to +70 °C).

The temperature range specified here (up to +100°C) only applies to sensors with part no. 2239**. -40 ... 100 °C (-40 ... 212 °F)

Storage temperature **Mechanical specifications**

Connection type Connection (system side) V18 connector PBT Housing material Sensing face PBT Degree of protection IP67

General information

Use in the hazardous area see instruction manuals Category 1G; 2G; 3G

Compliance with standards and directives

Standard conformity


NAMUR EN 60947-5-6:2000 IEC 60947-5-6:1999 NE 21:2007 Electromagnetic compatibility EN 60947-5-2:2007 Standards IEC 60947-5-2:2007

Approvals and certificates

cULus Listed, General Purpose **UL** approval CSA approval cCSAus Listed, General Purpose


CCC approval CCC approval / marking not required for products rated ≤36 V

Dimensions




Electrical Connection

N4-V18



Pinout



Wire colors in accordance with EN 60947-5-2

1	BN	(brown
2	WH	(white)
3	BU	(blue)
4	BK	(black)

FPEPPERL+FUCHS

ATEX 1G

Instruction

Device category 1G

EC-Type Examination Certificate

CE marking

ATEX marking

Directive conformity

Standards

Appropriate type

Effective internal capacitance Ci

Effective internal inductance L

General

Ambient temperature

Installation, commissioning

Maintenance

Special conditions

Protection from mechanical danger

Electrostatic charge

Manual electrical apparatus for hazardous areas

for use in hazardous areas with gas, vapour and mist

TÜV 99 ATEX 1479 X

€0102

(Ex) II 1G Ex ia IIC T6...T1 Ga

94/9/EG

EN 60079-0:2012, EN 60079-11:2012, EN 60079-26:2007

Ignition protection "Intrinsic safety"

Use is restricted to the following stated conditions

NCN3-F31.-N4...

≤ 100 nF A cable length of 10 m is considered.

The value is applicable for one sensor circuit

 \leq 100 μ H A cable length of 10 m is considered.

The value is applicable for one sensor circuit.

The apparatus has to be operated according to the appropriate data in the data sheet and in this instruction manual.

The EC-Type Examination Certificate has to be observed. The special conditions must be adhered to!

Directive 94/9/EG and hence also EC-Type Examination Certificates apply in general only to the use of electrical apparatus under atmospheric conditions.

The use in ambient temperatures of > 60 °C was tested with regard to hot surfaces by the mentioned certification authority.

If the equipment is not used under atmospheric conditions, a reduction of the permissible minimum ignition energies may have to be taken into consideration.

The temperature ranges, according to temperature class, are given in the EC-Type Examination Certificate. The maximum permissible ambient temperature of the data sheet must be noted, in addition, the lower of the two values must be $\boldsymbol{maintained.}$ Note: Use the temperature table for category 1 !!! The 20 % reduction in accordance with EN 1127-1:2007 has already been accounted for in the temperature table for category 1.

Laws and/or regulations and standards governing the use or intended usage goal must be observed.

The intrinsic safety is only assured in connection with an appropriate related apparatus and according to the proof of intrinsic safety.

The associated apparatus must satisfy the requirements of category ia.

Due to the possible danger of ignition, which can arise due to faults and/or transient currents in the equipotential bonding system, galvanic isolation of the power supply and signal circuit is preferable. Associated apparatus without electrical isolation must only be used if the appropriate requirements of IEC 60079-14 are met. Install the device in such a way that the resin surface is not exposed to mechanical

hazards.

No changes can be made to apparatus, which are operated in hazardous areas. Repairs to these apparatus are not possible.

When used in the temperature range below -20 $^{\circ}\text{C}$ the sensor should be protected from knocks by the provision of an additional housing.

Additional requirements for gas group IIC. Avoid electrostatic charges that can cause electrostatic discharge when installing or operating the device. Information on electrostatic hazards can be found in the technical specification IEC/TS 60079-32-1.

ATEX 2G

Instruction

Device category 2G

EC-Type Examination Certificate CE marking

ATEX marking

Directive conformity

Standards

Appropriate type

Effective internal capacitance Ci

Effective internal inductance Li

General

Ambient temperature

Installation, commissioning

Maintenance

Special conditions

Protection from mechanical danger

Manual electrical apparatus for hazardous areas

for use in hazardous areas with gas, vapour and mist TÜV 99 ATEX 1479 X \mathbf{C} $\mathbf{\epsilon}$ 0102

⟨ы⟩ II 1G Ex ia IIC T6...T1 Ga

94/9/FG

EN 60079-0:2012, EN 60079-11:2012 Ignition protection "Intrinsic safety"

Use is restricted to the following stated conditions

NCN3-F31.-N4..

 \leq 100 nF ; a cable length of 10 m is considered. The value is applicable for one sensor circuit.

 \leq 100 μH ; a cable length of 10 m is considered. The value is applicable for one sensor circuit.

The apparatus has to be operated according to the appropriate data in the data sheet and in this instruction manual. The EC-Type Examination Certificate has to be observed. The special conditions must be adhered to!

observed. The special conditions must be adhered to!
Directive 94/9/EG and hence also EC-Type Examination Certificates apply in general only to the use of electrical apparatus under atmospheric conditions.

The use in ambient temperatures of > 60 °C was tested with regard to hot surfaces by the mentioned certification authority.

If the equipment is not used under atmospheric conditions, a reduction of the permissible minimum ignition energies may have to be taken into consideration.

The temperature ranges, according to temperature class, are given in the EC-Type Examination Certificate. The maximum permissible ambient temperature of the data sheet must be noted, in addition, the lower of the two values must be maintained.

Laws and/or regulations and standards governing the use or intended usage goal must be observed. The intrinsic safety is only assured in connection with an appropriate related apparatus and according to the proof of intrinsic safety. Install the device in such a way that the resin surface is not exposed to mechanical hazards.

No changes can be made to apparatus, which are operated in hazardous areas. Repairs to these apparatus are not possible.

When used in the temperature range below -20 $^{\circ}$ C the sensor should be protected from knocks by the provision of an additional housing.

ATEX 3G (ic)

Instruction

Device category 3G (ic)

Certificate of Compliance

CE marking

ATEX marking

Directive conformity

Standards

Effective internal capacitance Ci

Effective internal inductance Li

General

Installation, commissioning

Maintenance

Special conditions

Maximum permissible ambient temperature T_{Umax} at Ui = 20 V

for Pi=34 mW, Ii=25 mA, T6
for Pi=34 mW, Ii=25 mA, T5
for Pi=34 mW, Ii=25 mA, T4-T1
for Pi=64 mW, Ii=25 mA, T6
for Pi=64 mW, Ii=25 mA, T5
for Pi=64 mW, Ii=25 mA, T4-T1
for Pi=169 mW, Ii=52 mA, T6
for Pi=169 mW, Ii=52 mA, T5
for Pi=169 mW, Ii=52 mA, T5
Tor Pi=169 mW, Ii=52 mA, T4-T1
Protection from mechanical danger

Connection parts

Manual electrical apparatus for hazardous areas

for use in hazardous areas with gas, vapour and mist

PF 13 CERT 2895 X

€0102

II 3G Ex ic IIC T6...T1 Gc

94/9/EG

EN 60079-0:2012, EN 60079-11:2012 Ignition protection category "ic"

Use is restricted to the following stated conditions

≤ 100 nF; A cable length of 10 m is considered.

The value is applicable for one sensor circuit.

 $\leq 100~\mu H$; A cable length of 10 m is considered. The value is applicable for one sensor circuit.

The apparatus has to be operated according to the appropriate data in the data sheet and in this instruction manual. The data stated in the data sheet are restricted by this

operating instruction!
The special conditions must be observed!

Laws and/or regulations and standards governing the use or intended usage goal must be observed. The sensor must only be operated with energy-limited circuits, which satisfy the requirements of IEC 60079-11. The explosion group depends on the connected, energy-limited power supply circuits.

Install the device in such a way that the resin surface is not exposed to mechanical hazards.

No changes can be made to apparatus, which are operated in hazardous areas. Repairs to these apparatus are not possible.

Each sensor circuit van be operated with the stated maximum values.

70 °C (158 °F) 67 °C (158 °F) 70 °C (158 °F) 70 °C (158 °F)

The sensor must not be mechanically damaged.

When used in the temperature range below -20 °C the sensor should be protected

from knocks by the provision of an additional housing.

The connection parts are to be installed, such that a minimum protection class of IP20 is achieved, in accordance with IEC 60529.