

PeakTech® 3296 PROD-ID: P 3296

[BACK](#)
Analog Voltmeter - 0...0,1/1/10/100/1000V AC/DC

This new series of analog measuring instruments for the work on workbenches and in classrooms, the education and training area, these devices are especially for daily use in test and measurement work through the stable metal-case construction. Since no batteries are required it also eliminates the expense and hassle of changing batteries.

This analog voltmeter has a variety of voltage measuring ranges, from 0,1 V up to 1000 V for measurements in the AC Voltage and DC Voltage range. The connection is done by a 4mm safety socket, each one for the respective measuring range.

- High quality bench type instrument for the use schools and education
- For DC and AC voltage measurements
- Durable ABS plastic case
- No power supply required for measurement
- With mirror scale and 4 mm safety sockets.
- Protection class II
- Accessories: User Manual


PICTURES

- [3296_Front.jpg \(589.0 kB\)](#)
- [3296_Front_Freigestellt.jpg \(468.3 kB\)](#)
- [3296_L.jpg \(598.5 kB\)](#)
- [3296_L_freigestellt.jpg \(475.2 kB\)](#)
- [3296_R.jpg \(575.5 kB\)](#)
- [3296_R_freigestellt.jpg \(459.7 kB\)](#)

MANUAL

- [Anleitung_PeakTech_3296_-24042017.pdf \(449.1 kB\)](#)

DCV	0,1 / 1 / 10 / 100 / 1000 V DC
Accuracy	±1,5 % of fullscale
DCV	3 / 10 / 100 / 1000 V AC
Accuracy	±2,5 % of fullscale
Dimensions (WxHxD)	170 x 130 x 55 mm
EAN-13	4250569403903

